

§ 73.258

without commercial messages, and furnishing the same to stations interconnected so as to permit simultaneous broadcast by all or some of them. However, arrangements involving only stations under common ownership, or only the rebroadcast by one station of programming from another with no compensation other than a lump-sum payment by the station rebroadcasting, are not considered arrangements with a network organization. The term "arrangement" means any contract, arrangement or understanding, express or implied.

[42 FR 16422, Mar. 28, 1977, as amended at 57 FR 48333, Oct. 23, 1992]

§ 73.258 Indicating instruments.

(a) Each FM broadcast station shall be equipped with indicating instruments which conform with the specifications described in § 73.1215 for determining power by the indirect method; for indicating the relative amplitude of the transmission line radio frequency current, voltage, or power; and with such other instruments as are necessary for the proper adjustment, operation, and maintenance of the transmitting system.

(b) The function of each instrument shall be clearly and permanently shown in the instrument itself or on the panel immediately adjacent thereto.

(c) In the event that any one of these indicating instruments becomes defective when no substitute which conforms with the required specifications is available, the station may be operated without the defective instrument pending its repair or replacement for a period not in excess of 60 days without further authority of the FCC: *Provided that*, if the defective instrument is the transmission line meter of a station which determines the output power by the direct method, the operating power shall be determined by the indirect method in accordance with § 73.267(c) during the entire time the station is operated without the transmission line meter.

(d) If conditions beyond the control of the licensee prevent the restoration of the meter to service within the above allowed period, an informal letter request in accordance with § 73.3549

47 CFR Ch. I (10–1–23 Edition)

may be filed with the FCC, Attention: Audio Division, Media Bureau, in Washington, DC for such additional time as may be required to complete repairs of the defective instrument.

[41 FR 36818, Sept. 1, 1976, as amended at 48 FR 44805, Sept. 30, 1983; 50 FR 32416, Aug. 12, 1985; 63 FR 33876, June 22, 1998; 67 FR 13231, Mar. 21, 2002]

§ 73.267 Determining operating power.

(a) The operating power of each FM station is to be determined by either the direct or indirect method.

(b) Direct method. The direct method of power determination for an FM station uses the indications of a calibrated transmission line meter (responsive to relative voltage, current, or power) located at the RF output terminals of the transmitter. This meter must be calibrated whenever there is any indication that the calibration is inaccurate or whenever any component of the metering circuit is repaired or replaced. The calibration must cover, as a minimum, the range from 90% to 105% of authorized power. The meter calibration may be checked by measuring the power at the transmitter terminals while either:

(1) Operating the transmitter into the transmitting antenna, and determining actual operating power by the indirect method described in § 73.267(c); or

(2) Operating the transmitter into a load (of substantially zero reactance and a resistance equal to the transmission line characteristic impedance) and using an electrical device (within $\pm 5\%$ accuracy) or temperature and coolant flow indicator (within $\pm 4\%$ accuracy) to determine the power.

(3) The calibration must cover, as a minimum, the range from 90% to 105% of authorized power and the meter must provide clear indications which will permit maintaining the operating power within the prescribed tolerance or the meter shall be calibrated to read directly in power units.

(c) *Indirect method.* The operating power is determined by the indirect method by applying an appropriate factor to the input power to the last radio-frequency power amplifier stage of the transmitter, using the following formula:

Federal Communications Commission

§ 73.295

Transmitter output power = $E_p \times I_p \times F$

Where:

E_p = DC input voltage of final radio stage.

I_p = Total DC input current of final radio stage.

F = Efficiency factor.

(1) If the above formula is not appropriate for the design of the transmitter final amplifier, use a formula specified by the transmitter manufacturer with other appropriate operating parameters.

(2) The value of the efficiency factor, F , established for the authorized transmitter output power is to be used for maintaining the operating power, even though there may be some variation in F over the power operating range of the transmitter.

(3) The value of F is to be determined and a record kept thereof by one of the following procedures listed in order of preference:

(i) Using the most recent measurement data for calibration of the transmission line meter according to the procedures described in paragraph (b) of this section or the most recent measurements made by the licensee establishing the value of F . In the case of composite transmitters or those in which the final amplifier stages have been modified pursuant to FCC approval, the licensee must furnish the FCC and also retain with the station records the measurement data used as a basis for determining the value of F .

(ii) Using measurement data shown on the transmitter manufacturer's test data supplied to the licensee; *Provided*, That measurements were made at the authorized frequency and transmitter output power.

(iii) Using the transmitter manufacturer's measurement data submitted to the FCC for type acceptance and as shown in the instruction book supplied to the licensee.

(Secs. 4, 5, 303, 48 Stat., as amended, 1066, 1068, 1082 (47 U.S.C. 154, 155, 303))

[44 FR 58731, Oct. 11, 1979, as amended at 45 FR 28141, Apr. 28, 1980; 48 FR 38479, Aug. 24, 1983; 49 FR 4210, Feb. 3, 1984; 49 FR 49851, Dec. 24, 1984]

§ 73.277 Permissible transmissions.

(a) No FM broadcast licensee or permittee shall enter into any agreement,

arrangement or understanding, oral or written, whereby it undertakes to supply, or receives consideration for supplying, on its main channel a functional music, background music, or other subscription service (including storecasting) for reception in the place or places of business of any subscriber.

(b) The transmission (or interruption) of radio energy in the FM broadcast band is permissible only pursuant to a station license, program test authority, construction permit, or experimental authorization and the provisions of this part of the rules.

[29 FR 7471, June 10, 1964. Redesignated at 39 FR 38655, Nov. 1, 1974 and amended at 48 FR 28454, June 22, 1983]

§ 73.293 Use of FM multiplex subcarriers.

Licensees of FM broadcast stations may transmit, without further authorization, subcarrier communication services in accordance with the provisions of §§ 73.319 and 73.322.

[51 FR 17028, May 8, 1986]

§ 73.295 FM subsidiary communications services.

(a) Subsidiary communication services are those transmitted on a subcarrier within the FM baseband signal, but do not include services which enhance the main program broadcast service, or exclusively relate to station operations (see § 73.293). Subsidiary communications include, but are not limited to services such as functional music, specialized foreign language programs, radio reading services, utility load management, market and financial data and news, paging and calling, traffic control signal switching, bilingual television audio, and point to point or multipoint messages.

(b) FM subsidiary communications services that are common carrier in nature are subject to common carrier regulation. Licensees operating such services are required to apply to the FCC for the appropriate authorization and to comply with all policies and rules applicable to the service. Responsibility for making the initial determinations of whether a particular activity is common carriage rests with the FM station licensee. Initial determinations by licensees are subject to